
## **MODULIGHTOR**

# Wagnetron - W1 - 5W LED LAMP


JOB - CLIENT - LOCATION

**DESCRIPTION** 

Notes



#### **Actual Size**



#### **PERFORMANCE -**

Power consumption 5 Watts
500 Total lumens
360 Degree light distribution
CBCP matches standard halogen lamps
Single light source
Single crisp shadow
Dimmable to 10%
Power Factor: 0.93
120VAC

#### **COLOR**

CCT: 2700K / 3000K
CRI> 80
White point accuracy within 3 SDCM
Rich saturated color rendering
Excellent color stability

#### **OPTIMIZED FORM**

Dimensions .8" X 2.42" / 21mm X 62mm Proprietary ceramic design provides superior thermal dissipation



#### LONG LIFE, LOW MAINTENANCE

Three year warranty

#### **ENERGY EFFICIENT**

Saves over 75-80% of energy compared to standard halogen lamps

#### INTENDED USE AND APPLICATIONS

LED retrofit lamp to replace 120VAC halogen lamps in Modulightor linear systems art lights, chandeliers, wall sconces and other indoor applications.

### **HIGHLY COMPATIBLE**

Works with most forward phase dimming controls and systems. Although we have tested on most systems we do recommend site specific testing. LED's are not a direct replacement for incandescent and halogen light (see our technical papers) but they are a fantastic alternative

**For more information** and comparative theory of LED and other light sources, visit us at www.modulightor.com/technical

Modulightor is doing its part to design, manufacture and build instillations responsibly with your help.

Thanks for coming -